

A1 Microwave

Web: <http://www.A1Microwave.com>

Email: A1sales@A1Microwave.com



A1 Microwave is a leading designer and manufacturer of filters, diplexers, power combiners, couplers and adaptors for satcoms, telecoms, radar, medical and scientific applications.

A1 Microwave also provides standard and custom waveguide components and assemblies including : straights, bends, twists and flexibles.

A1 Microwave is ITAR free and provides a **Fast delivery and No NRE** (on standard designs) by using sophisticated in-house design and simulation software, all new **designs are "right first time"** allowing the design to move from the design computer to the machine shop without the need for prototyping. **Stock filters available for immediate despatch.**

A1 Microwave has full in house CNC machining, turning, brazing, hard and soft soldering and bending facilities.



Ordering information :- Model number **PB1015CB** X-band Satcoms Upconverter Filter

Designed for X band satcoms upconverter applications for suppressing LO leakage from the mixer.

Passband 7.9 to 8.4 GHz
 Passband insertion loss 0.8 dB typical
 Passband return loss 18 dB min

Rejection : from DC to 6.5 GHz 90 dB min
 from 6.5 to 7.45 GHz 65 dB min
 from 8.7 to 9.2 GHz 45 dB min
 from 9.2 to 20 GHz 80 dB min

Overall length 124 mm nominal
 Connectors SMA female

