

A1 Microwave

Web: <http://www.A1Microwave.com>

Email: A1sales@A1Microwave.com



A1 Microwave is a leading designer and manufacturer of filters, diplexers, power combiners, couplers and adaptors for satcoms, telecoms, radar, medical and scientific applications.

A1 Microwave also provides standard and custom waveguide components and assemblies including : straights, bends, twists and flexibles.

A1 Microwave is ITAR free and provides a **Fast delivery and No NRE** (on standard designs) by using sophisticated in-house design and simulation software, all new **designs are "right first time"** allowing the design to move from the design computer to the machine shop without the need for prototyping. **Stock filters available for immediate despatch.**

A1 Microwave has full in house CNC machining, turning, brazing, hard and soft soldering and bending facilities.



Ordering information :- Model number **PB1733CB** K-band Satcom Downconverter Filter

Designed for K band satcoms downconverter applications for suppressing LO leakage from the mixer.

Passband	20.2 to 21.2 GHz
Passband insertion loss	1.4 dB max
Passband return loss	18 dB min
Passband group delay variation	1.5 ns max
Rejection: from DC to 19.6 GHz	55 dB min
from 21.8 to 34 GHz	40 dB min
Overall length	100 mm max
Connectors	SMA female + male (alternative flanges and coax interfaces available)

