


# A1 Microwave

Web: <http://www.A1Microwave.com>

Email: [A1sales@A1Microwave.com](mailto:A1sales@A1Microwave.com)



A1 Microwave is a leading designer and manufacturer of filters, diplexers, power combiners, couplers and adaptors for satcoms, telecoms, radar, medical and scientific applications.

A1 Microwave also provides standard and custom waveguide components and assemblies including : straights, bends, twists and flexibles.

A1 Microwave is ITAR free and provides a **Fast delivery and No NRE** (on standard designs) by using sophisticated in-house design and simulation software, all new **designs are "right first time"** allowing the design to move from the design computer to the machine shop without the need for prototyping. **Stock filters available for immediate despatch.**

A1 Microwave has full in house CNC machining, turning, brazing, hard and soft soldering and bending facilities.



## Ordering information :- Model number **PB1951WB Ka-band Satcoms Filter, in WG21**

Designed for Ka-band Satcoms Transmitter applications for suppressing Local Oscillator and other signals

Passband 24.65 to 25.25 GHz

Passband insertion loss 0.6 dB typical

Passband return loss 18 dB min

Rejection: from DC to 23.5 GHz 60 dB min  
from 27 to 33 GHz 60 dB min

Overall length 71.2 mm

Connectors K type female

Flange PBR 260

(see web site for alternative connectors, flanges and paint codes)

