

A1 Microwave

Web: <http://www.A1Microwave.com>

Email: A1sales@A1Microwave.com



A1 Microwave is a leading designer and manufacturer of filters, diplexers, power combiners, couplers and adaptors for satcoms, telecoms, radar, medical and scientific applications.

A1 Microwave also provides standard and custom waveguide components and assemblies including : straights, bends, twists and flexibles.

A1 Microwave is ITAR free and provides a **Fast delivery and No NRE** (on standard designs) by using sophisticated in-house design and simulation software, all new **designs are "right first time"** allowing the design to move from the design computer to the machine shop without the need for prototyping. **Stock filters available for immediate despatch.**

A1 Microwave has full in house CNC machining, turning, brazing, hard and soft soldering and bending facilities.



Ordering information :- Model number **PB1484WA-UB/UB-B** Ku-band Satcom receive radar reject filter

Designed for Ku band satcoms to protect receivers from unwanted interference from radars.

| | |
|--------------------------------|-------------------------------|
| Passband | 10.95 to 12.75 GHz |
| Passband insertion loss | 0.1 dB max |
| Passband return loss | 23 dB typical, 20 dB min |
| Passband group delay variation | 0.8 ns typical |
| Rejection: | from DC to 9.5 GHz 75 dB min |
| | from 9.5 to 10 GHz 55 dB min |
| | from 10 to 10.5 GHz 25 dB min |

Length of straight line filter 120 mm nominal,

Flanges UBR 120

(see web site for alternative flange, connectors and paint codes)

