

A1 Microwave

Web: <http://www.A1Microwave.com>

Email: A1sales@A1Microwave.com



A1 Microwave is a leading designer and manufacturer of filters, diplexers, power combiners, couplers and adaptors for satcoms, telecoms, radar, medical and scientific applications.

A1 Microwave also provides standard and custom waveguide components and assemblies including : straights, bends, twists and flexibles.

A1 Microwave is ITAR free and provides a **Fast delivery and No NRE** (on standard designs) by using sophisticated in-house design and simulation software, all new **designs are "right first time"** allowing the design to move from the design computer to the machine shop without the need for prototyping. **Stock filters available for immediate despatch.**

A1 Microwave has full in house CNC machining, turning, brazing, hard and soft soldering and bending facilities.



Ordering information :- Model number **PB1051IB** Satcoms Block downconverter IF Filter

Designed for satcoms block converter applications for suppressing LO leakage from the mixer.

Passband	950 to 1450 MHz
Passband insertion loss	0.3 dB typical
Passband group delay variation	1.9 nS typical
Rejection :	
from DC to 800 MHz	30 dB min
from 1.6 to 2 GHz	25 dB min
2 GHz to 2.7 GHz	80 dB min
Dimensions	100 x 75 x 25 mm nominal
Connectors	SMA female

