

# A1 Microwave

Web: <http://www.A1Microwave.com>

Email: [A1sales@A1Microwave.com](mailto:A1sales@A1Microwave.com)




A1 Microwave is a leading designer and manufacturer of filters, diplexers, power combiners, couplers and adaptors for satcoms, telecoms, radar, medical and scientific applications.

A1 Microwave also provides standard and custom waveguide components and assemblies including : straights, bends, twists and flexibles.

A1 Microwave is ITAR free and provides a **Fast delivery and No NRE** (on standard designs) by using sophisticated in-house design and simulation software, all new **designs are "right first time"** allowing the design to move from the design computer to the machine shop without the need for prototyping. **Stock filters available for immediate despatch.**

A1 Microwave has full in house CNC machining, turning, brazing, hard and soft soldering and bending facilities.



Ordering information :- Model number **PB1579WA** X-band Satcoms TX Reject Filter with circulator.

Designed for X band satcoms receiver applications for suppressing Transmit band signals.

Passband 7.25 to 7.75 GHz

Passband insertion loss 0.35 dB typical

Passband return loss 19 dB typical

Rejection : from 7.9 to 8.4 GHz 90 dB min

Overall length 232 mm nominal

Flanges Custom flanges

(see web site for alternative flanges and paint codes)

