

A1 Microwave

Web: <http://www.A1Microwave.com>

Email: A1sales@A1Microwave.com




A1 Microwave is a leading designer and manufacturer of filters, diplexers, power combiners, couplers and adaptors for satcoms, telecoms, radar, medical and scientific applications.

A1 Microwave also provides standard and custom waveguide components and assemblies including : straights, bends, twists and flexibles.

A1 Microwave is ITAR free and provides a **Fast delivery and No NRE** (on standard designs) by using sophisticated in-house design and simulation software, all new **designs are "right first time"** allowing the design to move from the design computer to the machine shop without the need for prototyping. **Stock filters available for immediate despatch.**

A1 Microwave has full in house CNC machining, turning, brazing, hard and soft soldering and bending facilities.



Ordering information :- Model number **PB1667WB** X-band Satcoms TX Reject Filter,

Designed for X band satcoms receiver applications for suppressing Transmit band signals.

Passband	7.25 to 7.75 GHz
Passband insertion loss	0.3 dB typical, 0.45 dB max
Passband return loss	20 dB min
Rejection :	from 7.9 to 8.4 GHz
	80 dB min
Overall length	180 mm nominal
Flanges	UBR 84 and PBR 84
	(see web site for alternative flanges and paint codes)

