

A1 Microwave

Web: <http://www.A1Microwave.com>

Email: A1sales@A1Microwave.com



A1 Microwave is a leading designer and manufacturer of filters, diplexers, power combiners, couplers and adaptors for satcoms, telecoms, radar, medical and scientific applications.

A1 Microwave also provides standard and custom waveguide components and assemblies including : straights, bends, twists and flexibles.

A1 Microwave is ITAR free and provides a **Fast delivery and No NRE** (on standard designs) by using sophisticated in-house design and simulation software, all new **designs are "right first time"** allowing the design to move from the design computer to the machine shop without the need for prototyping. **Stock filters available for immediate despatch.**

A1 Microwave has full in house CNC machining, turning, brazing, hard and soft soldering and bending facilities.



Ordering information :- Model number **PB1332WB** Bandpass Filter

Designed to have a very broad passband while rejecting close in spurious signals

Passband	26 to 36 GHz
Passband insertion loss	0.2 dB typical
Passband return loss	18 dB min
Rejection:	
from 21 to 24 GHz	40 dB min
from 38 to 40 GHz	40 dB min
Overall length	120 mm nominal
Flanges	UBR 320 (alternatives available)

