

A1 Microwave

Web: <http://www.A1Microwave.com>

Email: A1sales@A1Microwave.com




A1 Microwave is a leading designer and manufacturer of filters, diplexers, power combiners, couplers and adaptors for satcoms, telecoms, radar, medical and scientific applications.

A1 Microwave also provides standard and custom waveguide components and assemblies including : straights, bends, twists and flexibles.

A1 Microwave is ITAR free and provides a **Fast delivery and No NRE** (on standard designs) by using sophisticated in-house design and simulation software, all new **designs are "right first time"** allowing the design to move from the design computer to the machine shop without the need for prototyping. **Stock filters available for immediate despatch.**

A1 Microwave has full in house CNC machining, turning, brazing, hard and soft soldering and bending facilities.



Ordering information :- Model number **PB1451WH** K-band Satcoms transmit Filter

Designed for K band satcoms transmitter applications for suppressing receive band signals.

Passband	29.5 to 31 GHz
Passband insertion loss	0.2 dB max
Passband return loss	22 dB min

Rejection: from 19.7 to 21.2 GHz	90 dB min
----------------------------------	-----------

Overall length	75 mm
----------------	-------

Flanges	UBR 320
---------	---------

(see web site for alternative flange, connectors and paint codes)

