

A1 Microwave

Web: <http://www.A1Microwave.com>

Email: A1sales@A1Microwave.com



A1 Microwave is a leading designer and manufacturer of filters, diplexers, power combiners, couplers and adaptors for satcoms, telecoms, radar, medical and scientific applications.

A1 Microwave also provides standard and custom waveguide components and assemblies including : straights, bends, twists and flexibles.

A1 Microwave is ITAR free and provides a **Fast delivery and No NRE** (on standard designs) by using sophisticated in-house design and simulation software, all new **designs are "right first time"** allowing the design to move from the design computer to the machine shop without the need for prototyping. **Stock filters available for immediate despatch.**

A1 Microwave has full in house CNC machining, turning, brazing, hard and soft soldering and bending facilities.



Ordering information :- Model number **PB1658WH** Ka-band Satcoms transmit Filter

Designed for K band satcoms transmitter applications for suppressing receive band signals.

Passband 29.5 to 31 GHz

Passband insertion loss 0.2 dB max

Passband return loss 22 dB min

Rejection: from 19.7 to 21.2 GHz 90 dB min

Overall length 75 mm

Flanges UBR 320 + PBR 320

(see web site for alternative flange, connectors and paint codes)

