

A1 Microwave

Web: <http://www.A1Microwave.com>

Email: A1sales@A1Microwave.com



A1 Microwave is a leading designer and manufacturer of filters, diplexers, power combiners, couplers and adaptors for satcoms, telecoms, radar, medical and scientific applications.

A1 Microwave also provides standard and custom waveguide components and assemblies including : straights, bends, twists and flexibles.

A1 Microwave is ITAR free and provides a **Fast delivery and No NRE** (on standard designs) by using sophisticated in-house design and simulation software, all new **designs are "right first time"** allowing the design to move from the design computer to the machine shop without the need for prototyping. **Stock filters available for immediate despatch.**

A1 Microwave has full in house CNC machining, turning, brazing, hard and soft soldering and bending facilities.



Ordering information :- Model number **PB19971B**

Designed for suppressing local interference.

Passband	1925 to 2015 MHz
Passband insertion loss	0.5 dB typical, 1 dB max
Passband return loss	20 dB typical, 18 dB min
Rejection:	
at 1870 MHz	20 dB min
at 2070 MHz	20 dB min

Overall dimensions	100 x 50 x 17 mm nominal
Connectors	SMA female (alternative coax interfaces available)

