

# A1 Microwave

Web: <http://www.A1Microwave.com>

Email: [A1sales@A1Microwave.com](mailto:A1sales@A1Microwave.com)



A1 Microwave is a leading designer and manufacturer of filters, diplexers, power combiners, couplers and adaptors for satcoms, telecoms, radar, medical and scientific applications.

A1 Microwave also provides standard and custom waveguide components and assemblies including : straights, bends, twists and flexibles.

A1 Microwave is ITAR free and provides a **Fast delivery and No NRE** (on standard designs) by using sophisticated in-house design and simulation software, all new **designs are "right first time"** allowing the design to move from the design computer to the machine shop without the need for prototyping. **Stock filters available for immediate despatch.**

A1 Microwave has full in house CNC machining, turning, brazing, hard and soft soldering and bending facilities.



## Ordering information :- Model number **PB1063IB** Broadband IF Filter

Designed for IF for suppression of local oscillator leakage from the mixer and broad band noise.

Passband	2.6 to 3.4 GHz
Passband insertion loss	1.0 dB max
Passband group delay variation	2 nS typical

Rejection :	from DC to 2.2 GHz	70 dB min
	from 3.8 to 5.4 GHz	70 dB min

Overall length	100 mm nominal
Weight	105 g
Connectors	SMA female (alternatives available)

