

A1 Microwave

Web: <http://www.A1Microwave.com>

Email: A1sales@A1Microwave.com



A1 Microwave is a leading designer and manufacturer of filters, diplexers, power combiners, couplers and adaptors for satcoms, telecoms, radar, medical and scientific applications.

A1 Microwave also provides standard and custom waveguide components and assemblies including : straights, bends, twists and flexibles.

A1 Microwave is ITAR free and provides a **Fast delivery and No NRE** (on standard designs) by using sophisticated in-house design and simulation software, all new **designs are "right first time"** allowing the design to move from the design computer to the machine shop without the need for prototyping. **Stock filters available for immediate despatch.**

A1 Microwave has full in house CNC machining, turning, brazing, hard and soft soldering and bending facilities.



Ordering information :- Model number **PB1524WN** K-band Satcoms Receive Filter

Designed for K band satcoms receiver applications for suppressing transmit band signals.

Passband	18.2 to 22 GHz
Passband insertion loss	0.1 dB typical
Passband return loss	22 dB min
Passband group delay variation	0.1 ns max
Rejection:	from 27.5 to 30 GHz 90 dB typical, 80 dB min
Overall length	75 mm nominal
Flanges	PBR + UBR 220 (alternatives available)

