

A1 Microwave

Web: <http://www.A1Microwave.com>

Email: A1sales@A1Microwave.com




A1 Microwave is a leading designer and manufacturer of filters, diplexers, power combiners, couplers and adaptors for satcoms, telecoms, radar, medical and scientific applications.

A1 Microwave also provides standard and custom waveguide components and assemblies including : straights, bends, twists and flexibles.

A1 Microwave is ITAR free and provides a **Fast delivery and No NRE** (on standard designs) by using sophisticated in-house design and simulation software, all new **designs are "right first time"** allowing the design to move from the design computer to the machine shop without the need for prototyping. **Stock filters available for immediate despatch.**

A1 Microwave has full in house CNC machining, turning, brazing, hard and soft soldering and bending facilities.



Ordering information :- Model number **PB1897WN K-band Satcoms Receiver Filter**

Designed for K-band Satcoms Receiver applications for suppressing DBS and transmit band signals

Passband 19.2 to 21.2 GHz

Passband insertion loss 0.3 dB max

Passband return loss 22 dB typical

Rejection: from DC to 18.2 GHz 35 dB min

from 29 to 31 GHz 90 dB min

Overall length 80 mm

Flanges UBR 220 with clearance holes

