

A1 Microwave

Web: <http://www.A1Microwave.com>

Email: A1sales@A1Microwave.com



A1 Microwave is a leading designer and manufacturer of filters, diplexers, power combiners, couplers and adaptors for satcoms, telecoms, radar, medical and scientific applications.

A1 Microwave also provides standard and custom waveguide components and assemblies including : straights, bends, twists and flexibles.

A1 Microwave is ITAR free and provides a **Fast delivery and No NRE** (on standard designs) by using sophisticated in-house design and simulation software, all new **designs are "right first time"** allowing the design to move from the design computer to the machine shop without the need for prototyping. **Stock filters available for immediate despatch.**

A1 Microwave has full in house CNC machining, turning, brazing, hard and soft soldering and bending facilities.



Ordering information :- Model number **PB1912WB-UB/UB-B** Ku-band Satcom Transmit Filter

Bandpass filter designed for Ku band satcoms transmitter applications for suppressing broad band noise from the transmitter output.

Passband	13.75 to 14.5 GHz
Passband insertion loss	0.2 dB typical
Passband return loss	21 dB min
Rejection: from DC to 12.75 GHz	53 dB min
Overall length	3.25"
Flanges	UBR 120
	(see web site for alternative connectors, flanges and paint codes)

